

# AV Products Australia

Spec File



## MP906 & MP912 Matrix Mixer Amplifiers

### Features

- 4 Paging Stations
- 3 Balanced Mic Inputs
- 2 Aux/Mic Inputs
- 4 Speaker Zones

### Application

- Conferences /Meeting Rooms
- Bars/Restaurant's
- Schools

### Description

Matrix mixer amplifiers with 4 x 60watt or 120watt amplifiers. Up to 4 dedicated CM12 paging stations via Cat5/6 cabling, 3 XLR balanced microphone inputs. 2 unbalanced aux/mic inputs. Balanced inputs have phantom supply. Playback from USB of MP3 files and Bluetooth. Built in chime and alarm.

Each inputs can be directed to independently to each output (matrix). Each input has independent bass and treble controls  
4 Line level balanced output are provided if a larger amplifier is needed.



### Specification –

	MP906	MP912
Rated Output	4 x 60watt	4 x 120watt
Speaker Output	4Ω, 70V and 100Volt	4Ω, 70V and 100Volt
Zone	4 independent zones	4 independent zones
Inputs	4 Paging station 3 Balanced Mic with trim and ptm 2 Aux Line USB MP3 playback Bluetooth	4 Paging station 3 Balanced Mic with trim and ptm 2 Aux Line USB MP3 playback Bluetooth
Frequency Response	80hz – 16khz	80hz – 16khz
S/N Ratio	>75dB	>75dB
Tone Controls	Bass +/-8dB 100hz Treble +/-8dB 10Khz	Bass +/-8dB 100hz Treble +/-8dB 10Khz
Protection	AC Fuse DC Fuse Overload, Shot circuit, Temperature	AC Fuse DC Fuse Overload, Shot circuit, Temperature
Dimensions	483Wx440Dx132H	483Wx440Dx132H
Weight	25.5kg	28kg

**AV Products Australia**  
PO Box R592  
Royal Exchange 1225  
**Phone:** +61 2 9241 1884  
**Web:** [www.avpau.com](http://www.avpau.com)  
**E-mail:** [slaes@avpau.com](mailto:slaes@avpau.com)